arXiv:0801.2991v1 [math.PR] 18 Jan 2008

A NEW CONCEPT OF STRONG CONTROLLABILITY VIA THE SCHUR COMPLEMENT IN ADAPTIVE TRACKING

BERNARD BERCU AND VICTOR VAZQUEZ

Abstract. We propose a new concept of strong controllability associated with the Schur complement of a suitable limiting matrix. This concept allows us to extend the previous results associated with multidimensional ARX models. On the one hand, we carry out a sharp analysis of the almost sure convergence for both least squares and weighted least squares algorithms. On the other hand, we also provide a central limit theorem and a law of iterated logarithm for these two stochastic algorithms. Our asymptotic results are illustrated by numerical simulations.

1. Introduction

Consider the d-dimensional autoregressive process with adaptive control of order (p, q), $\text{ARX}_d(p, q)$ for short, given for all $n \geq 0$ by

$$A(R)X_{n+1} = B(R)U_n + \varepsilon_{n+1} \tag{1.1}$$

where R stands for the shift-back operator and X_n, U_n and ε_n are the system output, input and driven noise, respectively. The polynomials A and B are given for all $z \in \mathbb{C}$ by

$$\begin{aligned} A(z) &= I_d - A_1 z - \cdots - A_p z^p, \\ B(z) &= I_d + B_1 z + \cdots + B_q z^q, \end{aligned}$$

where A_i and B_j are unknown square matrices of order d and I_d is the identity matrix. Denote by θ the unknown parameter of the model

$$\theta^t = (A_1, \ldots, A_p, B_1, \ldots, B_q).$$

Relation (1.1) can be rewritten as

$$X_{n+1} = \theta^t \Phi_n + U_n + \varepsilon_{n+1} \tag{1.2}$$

where the regression vector $\Phi_n = \left(X_n^p, U_{n-1}^q\right)^t$ with $X_n^p = (X_n^t, \ldots, X_{n-p+1}^t)$ and $U_n^q = (U_n^t, \ldots, U_{n-q+1}^t)$. In all the sequel, we shall assume the (ε_n) is a martingale difference sequence adapted to the filtration $\mathbb{F} = (\mathcal{F}_n)$ where $\mathcal{F}_n$ stands for the σ-algebra of the events occurring up to time n. We also assume that, for all $n \geq 0$, $\mathbb{E}[\varepsilon_{n+1}\varepsilon_{n+1}^t|\mathcal{F}_n] = \Gamma$ a.s. where Γ is a positive definite deterministic covariance matrix.

A wide literature concerning the estimation of θ as well as on the tracking control is available, [1], [4], [5], [7], [8], [10], [12], [15]. The purpose of this paper is to establish sharp asymptotic results for stochastic algorithms associated with the estimation

---

2000 *Mathematics Subject Classification.* Primary: 62G05 Secondary: 93C40, 15A09, 60F05, 60F15.

Key words and phrases. Estimation, adaptive control, Schur complement, central limit theorem, law of iterated logarithm.

of θ via the introduction of a new concept of strong controllability. The strong controllability is closely related to the almost sure convergence of the matrix

$$S_n = \sum_{k=0}^{n} \Phi_k \Phi_k^t.$$

In the particular case $q = 0$, it was shown in [5] that

$$\lim_{n\to\infty} \frac{S_n}{n} = L \quad \text{a.s.}$$

where L is the block diagonal matrix of order dp given by

$$L = \operatorname{diag}(\Gamma, \cdots, \Gamma).$$

Under the classical causality assumption, we shall now prove that

$$\lim_{n\to\infty} \frac{S_n}{n} = \Lambda \quad \text{a.s.} \tag{1.3}$$

where Λ is the symmetric square matrix of order $\delta = d(p+q)$

$$\Lambda = \begin{pmatrix} L & K^t \\ K & H \end{pmatrix}$$

and the matrices H and K will be explicitly calculated. It is well-known [14] that $\det(\Lambda) = \det(L)\det(S)$ where $S = H - KL^{-1}K^t$ is the Schur complement of L in Λ. Moreover, as L is positive definite, Λ is positive definite if and only if S is positive definite. Via our new concept of strong controllability, we shall propose a suitable assumption under which S is positive definite. It will allow us to improve the previous results [5], [6], [10], [11] by showing a central limit theorem (CLT) and a law of iterated logarithm (LIL) for both the least squares (LS) and the weighted least squares (WLS) algorithms associated with the estimation of θ.

The paper is organized as follows. Section 2 is devoted to the introduction of our new concept of strong controllability together with some linear algebra calculations. Section 3 deals with the parameter estimation and the adaptive control. In Section 4, we establish convergence (1.3) and we deduce a CLT as well as a LIL for both LS and WLS algorithms. Some numerical simulations are provided in Section 5. A short conclusion is given in Section 6. All technical proofs are postponed in the Appendices.

2. STRONG CONTROLLABILITY

In all the sequel, we shall make use of the well-known causality assumption on B. More precisely, we assume that for all $z \in \mathbb{C}$ with $|z| \leq 1$

$$\det(B(z)) \neq 0. \tag{A$_1$}$$

In other words, the polynomial $\det(B(z))$ only has zeros with modulus > 1. Consequently, if $r > 1$ is strictly less than the smallest modulus of the zeros of $\det(B(z))$, then $B(z)$ is invertible in the ball with center zero and radius r and $B^{-1}(z)$ is a holomorphic function (see e.g. [9] page 155). For all $z \in \mathbb{C}$ such that $|z| \leq r$, we shall denote

$$P(z) = B^{-1}(z)(A(z) - I_d) = \sum_{k=1}^{\infty} P_k z^k. \tag{2.1}$$

All the matrices P_k may be explicitly calculated as functions of the matrices A_i and B_j. For example, $P_1 = -A_1$, $P_2 = B_1A_1 - A_2$, $P_3 = (B_2 - B_1^2)A_1 + B_1A_2 - A_3$. We shall often make use of the square matrix of order dq given, if $p \geq q$, by

$$\Pi = \begin{pmatrix} P_p & P_{p+1} & \cdots & P_{p+q-2} & P_{p+q-1} \\ P_{p-1} & P_p & P_{p+1} & \cdots & P_{p+q-2} \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ P_{p-q+2} & \cdots & P_{p-1} & P_p & P_{p+1} \\ P_{p-q+1} & P_{p-q+2} & \cdots & P_{p-1} & P_p \end{pmatrix}$$

while, if $p \leq q$, by

$$\Pi = \begin{pmatrix} P_p & P_{p+1} & \cdots & \cdots & P_{p+q-2} & P_{p+q-1} \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ P_1 & P_2 & \cdots & \cdots & P_{q-1} & P_q \\ 0 & P_1 & P_2 & \cdots & P_{q-2} & P_{q-1} \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & \cdots & 0 & P_1 & \cdots & P_p \end{pmatrix}.$$

Definition 2.1. An $\text{ARX}_d(p,q)$ is said to be strongly controllable if B is causal and Π is invertible,

$$\det(\Pi) \neq 0. \tag{A$_2$}$$

Remark 2.1. The concept of strong controllability is not really restrictive. For example, if $p = q = 1$, assumption (A_2) reduces to $\det(A_1) \neq 0$, if $p = 2$, $q = 1$ to $\det(A_2 - B_1A_1) \neq 0$, if $p = 1$, $q = 2$ to $\det(A_1) \neq 0$, while if $p = q = 2$ to

$$\det \begin{pmatrix} A_1 & A_2 - B_1A_1 \\ A_2 - B_1A_1 & A_3 - B_1A_2 + (B_1^2 - B_2)A_1 \end{pmatrix} \neq 0.$$

For all $1 \leq i \leq q$, denote by H_i be the square matrix of order d

$$H_i = \sum_{k=i}^{\infty} P_k \Gamma P_{k-i+1}^t.$$

In addition, let H be the symmetric square matrix of order dq

$$H = \begin{pmatrix} H_1 & H_2 & \cdots & H_{q-1} & H_q \\ H_2^t & H_1 & H_2 & \cdots & H_{q-1} \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ H_{q-1}^t & \cdots & H_2^t & H_1 & H_2 \\ H_q^t & H_{q-1}^t & \cdots & H_2^t & H_1 \end{pmatrix}. \tag{2.2}$$

For all $1 \leq i \leq p$, let $K_i = P_i\Gamma$ and denote by K the rectangular matrix of dimension $dq \times dp$ given, if $p \geq q$, by

$$K = \begin{pmatrix} 0 & K_1 & K_2 & \cdots & \cdots & K_{p-2} & K_{p-1} \\ 0 & 0 & K_1 & \cdots & \cdots & K_{p-3} & K_{p-2} \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & \cdots & 0 & K_1 & K_2 & \cdots & K_{p-q+1} \\ 0 & \cdots & \cdots & 0 & K_1 & \cdots & K_{p-q} \end{pmatrix}$$

while, if $p \leq q$, by

$$K = \begin{pmatrix} 0 & K_1 & \cdots & K_{p-2} & K_{p-1} \\ 0 & 0 & K_1 & \cdots & K_{p-2} \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & \cdots & 0 & 0 & K_1 \\ 0 & 0 & \cdots & 0 & 0 \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & 0 & \cdots & 0 & 0 \end{pmatrix}.$$

Finally, let L be the block diagonal matrix of order dp

$$L = \begin{pmatrix} \Gamma & 0 & \cdots & 0 & 0 \\ 0 & \Gamma & 0 & \cdots & 0 \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & \cdots & 0 & \Gamma & 0 \\ 0 & 0 & \cdots & 0 & \Gamma \end{pmatrix} \tag{2.3}$$

and denote by Λ the symmetric square matrix of order $\delta = d(p+q)$

$$\Lambda = \begin{pmatrix} L & K^t \\ K & H \end{pmatrix}. \tag{2.4}$$

The following lemma is the keystone of all our asymptotic results.

Lemma 2.2. Let S be the Schur complement of L in Λ

$$S = H - KL^{-1}K^t. \tag{2.5}$$

If (A$_1$) and (A$_2$) hold, S and Λ are invertible and

$$\Lambda^{-1} = \begin{pmatrix} L^{-1} + L^{-1}K^tS^{-1}KL^{-1} & -L^{-1}K^tS^{-1} \\ -S^{-1}KL^{-1} & S^{-1} \end{pmatrix}. \tag{2.6}$$

Proof. The proof is given in Appendix A. □

3. Estimation and Adaptive control

First of all, we focus our attention on the estimation of the parameter θ. We shall make use of the weighted least squares (WLS) algorithm introduced by Bercu and Duflo [3], [4], which satisfies, for all $n \geq 0$,

$$\widehat{\theta}_{n+1} = \widehat{\theta}_n + a_n S_n^{-1}(a)\Phi_n \left(X_{n+1} - U_n - \widehat{\theta}_n^t \Phi_n \right)^t \tag{3.1}$$

where the initial value $\hat{\theta}_0$ may be arbitrarily chosen and

$$S_n(a) = \sum_{k=0}^{n} a_k \Phi_k \Phi_k^t + I_\delta$$

where the identity matrix I_δ with $\delta = d(p+q)$ is added in order to avoid useless invertibility assumption. The choice of the weighted sequence (a_n) is crucial. If

$$a_n = 1$$

we find again the standard LS algorithm, while if $\gamma > 0$,

$$a_n = \Big(\frac{1}{\log s_n} \Big)^{1+\gamma} \qquad \text{with} \qquad s_n = \sum_{k=0}^{n} ||\Phi_k||^2,$$

we obtain the WLS algorithm of Bercu and Duflo.

Next, we are concern with the choice of the adaptive control U_n. The crucial role played by U_n is to regulate the dynamic of the process (X_n) by forcing X_n to track step by step a predictable reference trajectory x_n. We shall make use of the adaptive tracking control proposed by Aström and Wittenmark [1] given, for all $n \geq 0$, by

$$U_n = x_{n+1} - \widehat{\theta}_n^{\,t}\,\Phi_n. \tag{3.2}$$

By substituting (3.2) into (1.2), we obtain the closed-loop system

$$X_{n+1} - x_{n+1} = \pi_n + \varepsilon_{n+1} \tag{3.3}$$

where the prediction error $\pi_n = (\theta - \widehat{\theta}_n)^t\Phi_n$. In all the sequel, we assume that the reference trajectory (x_n) satisfies

$$\sum_{k=1}^{n} \| x_k \|^2 = o(n) \qquad \text{a.s.} \tag{3.4}$$

In addition, we also assume that the driven noise (ε_n) satisfies the strong law of large numbers which means that if

$$\Gamma_n = \frac{1}{n}\sum_{k=1}^{n} \varepsilon_k \varepsilon_k^t, \tag{3.5}$$

then Γ_n converges a.s. to Γ. That is the case if, for example, (ε_n) is a white noise or if (ε_n) has a finite conditional moment of order > 2. Finally, let (C_n) be the average cost matrix sequence defined by

$$C_n = \frac{1}{n}\sum_{k=1}^{n}(X_k - x_k)(X_k - x_k)^t.$$

The tracking is said to be optimal if C_n converges a.s. to Γ.

4. Main results

Our first result concerns the almost sure properties of the LS algorithm.

Theorem 4.1. *Assume that the $ARX_d(p, q)$ model is strongly controllable and that (ε_n) has finite conditional moment of order > 2. Then, for the LS algorithm, we have*

$$\lim_{n\to\infty} \frac{S_n}{n} = \Lambda \qquad \textit{a.s.} \tag{4.1}$$

where the limiting matrix Λ is given by (2.4). In addition, the tracking is optimal

$$\| C_n - \Gamma_n \| = \mathcal{O}\left(\frac{\log n}{n}\right) \qquad \textit{a.s.} \tag{4.2}$$

We can be more precise in (4.2) by

$$\lim_{n\to\infty} \frac{1}{\log n}\sum_{k=1}^{n}(X_k - x_k - \varepsilon_k)(X_k - x_k - \varepsilon_k)^t = \delta\Gamma \qquad \textit{a.s.} \tag{4.3}$$

Finally, $\widehat{\theta}_n$ converges almost surely to θ

$$\| \widehat{\theta}_n - \theta \|^2 = \mathcal{O}\left(\frac{\log n}{n}\right) \qquad \textit{a.s.} \tag{4.4}$$

Our second result is related to the almost sure properties of the WLS algorithm.

Theorem 4.2. *Assume that the $ARX_d(p,q)$ model is strongly controllable. In addition, suppose that either (ε_n) is a white noise or (ε_n) has finite conditional moment of order > 2. Then, for the WLS algorithm, we have*

$$\lim_{n\to\infty} (\log n)^{1+\gamma} \frac{S_n(a)}{n} = \Lambda \quad a.s. \tag{4.5}$$

where the limiting matrix Λ is given by (2.4). In addition, the tracking is optimal

$$\| C_n - \Gamma_n \| = o\left(\frac{(\log n)^{1+\gamma}}{n}\right) \quad a.s. \tag{4.6}$$

Finally, $\widehat{\theta}_n$ converges almost surely to θ

$$\| \widehat{\theta}_n - \theta \|^2 = \mathcal{O}\left(\frac{(\log n)^{1+\gamma}}{n}\right) \quad a.s. \tag{4.7}$$

Proof. The proof is given in Appendix B. □

Remark 4.1. One can observe that Theorems 4.1 and 4.2 extend the results of Bercu [5] and Guo [11] previously established in the AR framework.

Theorem 4.3. *Assume that the $ARX_d(p,q)$ model is strongly controllable and that (ε_n) has finite conditional moment of order $\alpha > 2$. In addition, suppose that (x_n) has the same regularity in norm as (ε_n) which means that for all $2 < \beta < \alpha$*

$$\sum_{k=1}^{n} \| x_k \|^{\beta} = \mathcal{O}(n) \quad a.s. \tag{4.8}$$

Then, the LS and WLS algorithms share the same central limit theorem

$$\sqrt{n}(\widehat{\theta}_n - \theta) \xrightarrow{\mathcal{L}} \mathcal{N}(0, \Lambda^{-1} \otimes \Gamma) \tag{4.9}$$

where the inverse matrix Λ^{-1} is given by (2.6) and the symbol $\otimes$ stands for the matrix Kronecker product. In addition, for any vectors $u \in \mathbb{R}^d$ and $v \in \mathbb{R}^{\delta}$, they also share the same law of iterated logarithm

$$\begin{aligned}\limsup_{n\to\infty} \left(\frac{n}{2\log\log n}\right)^{1/2} v^t(\widehat{\theta}_n - \theta)u &= -\liminf_{n\to\infty} \left(\frac{n}{2\log\log n}\right)^{1/2} v^t(\widehat{\theta}_n - \theta)u \\ &= \left(v^t\Lambda^{-1}v\right)^{1/2}\left(u^t\Gamma u\right)^{1/2} \quad a.s. \end{aligned} \tag{4.10}$$

In particular,

$$\left(\frac{\lambda_{min}\Gamma}{\lambda_{max}\Lambda}\right) \leq \limsup_{n\to\infty} \left(\frac{n}{2\log\log n}\right) \| \hat{\theta}_n - \theta \|^2 \leq \left(\frac{\lambda_{max}\Gamma}{\lambda_{min}\Lambda}\right) \quad a.s. \tag{4.11}$$

where $\lambda_{min}\Gamma$ and $\lambda_{max}\Gamma$ are the minimum and the maximum eigenvalues of Γ.

Proof. The proof is given in Appendix C. □

5. NUMERICAL SIMULATIONS

The goal of this section is to propose some numerical experiments for illustrating the asymptotic results of Section 4. In order to keep this section brief, we shall only focus our attention on a strongly controllable $ARX_d(p,q)$ model in dimension $d = 2$ with $p = 1$ and $q = 1$. Our numerical simulations are based on $M = 500$ realizations of sample size $N = 1000$. For the sake of simplicity, the reference trajectory (x_n) is chosen to be identically zero and the driven noise (ε_n) is a Gaussian $\mathcal{N}(0,1)$ white noise. Consider the $ARX_2(1,1)$ model

$$X_{n+1} = AX_n + U_n + BU_{n-1} + \varepsilon_{n+1}$$

where

$$A = \begin{pmatrix} 2 & 0 \\ 0 & 1 \end{pmatrix} \qquad \text{and} \qquad B = \frac{1}{4}\begin{pmatrix} 3 & 0 \\ 0 & -2 \end{pmatrix}.$$

Figure 1 shows the almost sure convergence of the LS estimator $\widehat{\theta}_n$ to the four coordinates of θ which are different from zero. One can observe that $\widehat{\theta}_n$ performs very well in the estimation of θ.



Figure 1. Left: LLN for A, Right: LLN for B.

Figure 2 shows the CLT for the four coordinates of

$$Z_N = \sqrt{N}\Lambda^{1/2}(\widehat{\theta}_N - \theta)$$

where Λ is the limiting matrix given by (2.4) with $L = I_2$, $K = 0$ and

$$H = A^2(I_2 - B^2)^{-1} = \frac{4}{21}\begin{pmatrix} 48 & 0 \\ 0 & 7 \end{pmatrix}.$$

One can realize that each component of Z_N has $\mathcal{N}(0,1)$ distribution as expected.



Figure 2. Left: CLT for A, Right: CLT for B.

6. Conclusion

Via our new concept of strong controllability, we have extended the analysis of the almost sure convergence for both LS and WLS algorithms in the multidimensional ARX framework. It enables us to provide a positive answer to a conjecture in [5] by establishing a CLT and a LIL for these two stochastic algorithms. In our approach, the leading matrix associated with the matrix polynomial B, commonly called the high frequency gain, was supposed to be known and it was chosen as the identity matrix I_d. It would be a great challenge for the control community to carry out similar analysis with unknown high frequency gain and to extend it to ARMAX models.

7. Appendix A.

Proof of Lemma 2.2. Let Σ be the infinite-dimensional diagonal square matrix

$$\Sigma = \begin{pmatrix} \Gamma & 0 & \cdots & \cdots & \cdots \\ 0 & \Gamma & 0 & \cdots & \cdots \\ \cdots & 0 & \Gamma & 0 & \cdots \\ \cdots & \cdots & \cdots & \cdots & \cdots \\ \cdots & \cdots & \cdots & \cdots & \cdots \end{pmatrix}.$$

Moreover, denote by T the infinite-dimensional rectangular matrix with dq raws and an infinite number of columns given, if $p \geq q$, by

$$T = \begin{pmatrix} P_p & P_{p+1} & \cdots & P_k & P_{k+1} & \cdots \\ P_{p-1} & P_p & \cdots & P_{k-1} & P_k & \cdots \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ P_{p-q+2} & P_{p-q+3} & \cdots & P_{k-q+2} & P_{k-q+3} & \cdots \\ P_{p-q+1} & P_{p-q+2} & \cdots & P_{k-q+1} & P_{k-q+2} & \cdots \end{pmatrix}$$

while, if $p \leq q$, by

$$T = \begin{pmatrix} P_p & P_{p+1} & \cdots & \cdots & P_k & P_{k+1} & \cdots \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ P_1 & P_2 & \cdots & \cdots & P_{k-p+1} & P_{k-p+2} & \cdots \\ 0 & P_1 & P_2 & \cdots & P_{k-p} & P_{k-p+1} & \cdots \\ \cdots & \cdots & \cdots & \cdots & \cdots & \cdots & \cdots \\ 0 & \cdots & \cdots & 0 & P_1 & P_2 & \cdots \end{pmatrix}.$$

After some straightforward, although rather lengthy, linear algebra calculations, it is possible to deduce from (2.5) that

$$S = T\Sigma T^t. \tag{A.1}$$

It clearly follows from this suitable decomposition that

$$\ker(S) = \ker(T^t). \tag{A.2}$$

As a matter of fact, assume that $v \in \mathbb{R}^{dq}$ belongs to $\ker(T^t)$. Then, $T^t v = 0$, $Sv = 0$ which leads to $\ker(T^t) \subset \ker(S)$. On the other hand, assume that $v \in \mathbb{R}^{dq}$ belongs to $\ker(S)$. Since $Sv = 0$, we clearly have $v^t S v = 0$, so $v^t T \Sigma T^t v = 0$. However, the matrix Γ is positive definite. Consequently, $T^t v = 0$ and $\ker(S) \subset \ker(T^t)$, which implies (A.2). Moreover, it follows from the well-known rank theorem that

$$dq = \dim(\ker(S)) + \operatorname{rank}(S). \tag{A.3}$$

As soon as $\ker(S) = \{0\}$, $\dim(\ker(S)) = 0$ and we obtain from (A.3) that S is of full rank dq which means that S is invertible. Furthermore, the left hand side square matrix of order dq of the infinite-dimensional matrix T is precisely Π. Consequently, if Π is invertible, Π is of full rank dq, $\ker(\Pi) = \ker(\Pi^t) = \{0\}$ and the left null space of T reduces to the null vector of $\mathbb{R}^{dq}$. Hence, if Π is invertible, we deduce from (A.2) together with (A.3) that S is also invertible. Finally, as

$$\det(\Lambda) = \det(L)\det(S) = \det(\Gamma)^p \det(S), \tag{A.4}$$

we obtain from (A.4) that Λ is invertible and formula (2.6) follows from [14] page 18, which completes the proof of Lemma 2.2. □

APPENDIX B.

Proof of Theorem 4.1. In order to prove Theorem 4.1, we shall make use of the same approach than Bercu [5] or Guo and Chen [10]. First of all, we recall that for all $n \geq 0$

$$X_{n+1} - x_{n+1} = \pi_n + \varepsilon_{n+1}. \tag{B.1}$$

In addition, let

$$s_n = \sum_{k=0}^{n} ||\Phi_k||^2.$$

It follows from (B.1) together with the strong law of large numbers for martingales (see e.g. Corollary 1.3.25 of [9]) that $n = \mathcal{O}(s_n)$ a.s. Moreover, by Theorem 1 of [2] or Lemma 1 of [10], we have

$$\sum_{k=1}^{n}(1 - f_k) \parallel \pi_k \parallel^2 = \mathcal{O}(\log s_n) \quad \text{a.s.} \tag{B.2}$$

where $f_n = \Phi_n^t S_n^{-1} \Phi_n$. Hence, if (ε_n) has finite conditional moment of order $\alpha > 2$, we can show by the causality assumption (A_1) on the matrix polynomial B together with (B.2) that $\parallel \Phi_n \parallel^2 = \mathcal{O}(s_n^\beta)$ a.s. for all $2\alpha^{-1} < \beta < 1$. In addition, let $g_n = \Phi_n^t S_{n-1}^{-1} \Phi_n$ and $\delta_n = \mathrm{tr}(S_{n-1}^{-1} - S_n^{-1})$. It is well-known that

$$(1 - f_n)(1 + g_n) = 1$$

and (δ_n) tends to zero a.s. Consequently, as $\parallel \pi_n \parallel^2 = (1 - f_n)(1 + g_n) \parallel \pi_n \parallel^2$ and $1 + g_n \leq 2 + \delta_n \parallel \Phi_n \parallel^2$, we can deduce from (B.2) that

$$\sum_{k=1}^{n} \parallel \pi_k \parallel^2 = o(s_n^\beta \log s_n) \quad \text{a.s.} \tag{B.3}$$

Therefore, we obtain from (3.4), (B.1) and (B.3) that

$$\sum_{k=1}^{n} \parallel X_{k+1} \parallel^2 = o(s_n^\beta \log s_n) + \mathcal{O}(n) \quad \text{a.s.} \tag{B.4}$$

Furthermore, we infer from assumption (A_1) that

$$U_n = B^{-1}(R)A(R)X_{n+1} - B^{-1}(R)\varepsilon_{n+1} \tag{B.5}$$

which implies by (B.4) that

$$\sum_{k=1}^{n} \parallel U_k \parallel^2 = o(s_n^\beta \log s_n) + \mathcal{O}(n) \quad \text{a.s.} \tag{B.6}$$

It remains to put together the two contributions (B.4) and (B.6) to deduce that $s_n = o(s_n) + \mathcal{O}(n)$ a.s. leading to $s_n = \mathcal{O}(n)$ a.s. Hence, it follows from (B.3) that

$$\sum_{k=1}^{n} \| \pi_k \|^2 = o(n) \quad \text{a.s.} \tag{B.7}$$

Consequently, we obtain from (3.4), (B.1) and (B.7) that

$$\lim_{n\to\infty} \frac{1}{n} \sum_{k=1}^{n} X_k X_k^t = \Gamma \quad \text{a.s.}$$

and, for all $1 \leq i \leq p-1$, $\displaystyle\sum_{k=0}^{n} X_k X_{k-i}^t = o(n)$ a.s. which implies that

$$\lim_{n\to\infty} \frac{1}{n} \sum_{k=1}^{n} X_k^p (X_k^p)^t = L \quad \text{a.s.} \tag{B.8}$$

where L is given by (2.3). Furthermore, it follows from relation (1.1) together with (B.1) and assumption (A$_1$) that, for all $n \geq 0$,

$$\begin{aligned} U_n &= B^{-1}(R)A(R)X_{n+1} - B^{-1}(R)\varepsilon_{n+1}, \\ &= B^{-1}(R)A(R)(\pi_n + x_{n+1}) + B^{-1}(R)(A(R) - I_d)\varepsilon_{n+1}, \\ &= V_n + W_{n+1}. \end{aligned}$$

Consequently, as $W_n = P(R)\varepsilon_n$, we deduce from (3.4), (B.7) and the strong law of large numbers for martingales (see e.g. Theorem 4.3.16 of [9]) that, for all $1 \leq i \leq q$,

$$\lim_{n\to\infty} \frac{1}{n} \sum_{k=1}^{n} U_k U_{k-i+1}^t = H_i \quad \text{a.s.}$$

which ensures that

$$\lim_{n\to\infty} \frac{1}{n} \sum_{k=1}^{n} U_k^q (U_k^q)^t = H \quad \text{a.s.} \tag{B.9}$$

where H is given by (2.2). Via the same lines, we also find that

$$\lim_{n\to\infty} \frac{1}{n} \sum_{k=1}^{n} X_k^p (U_{k-1}^q)^t = K^t \quad \text{a.s.} \tag{B.10}$$

Therefore, it follows from the conjunction of (B.8), (B.9) and (B.10) that

$$\lim_{n\to\infty} \frac{S_n}{n} = \Lambda \quad \text{a.s.} \tag{B.11}$$

where the limiting matrix Λ is given by (2.4). Hereafter, we recall that the ARX$_d(p,q)$ model is strongly controllable. Thanks to Lemma 2.2, the matrix Λ is invertible and Λ^{-1}, given by (2.6), may be explicitly calculated. This is the key point for the rest of the proof. On the one hand, it follows from (B.11) that $n = \mathcal{O}(\lambda_{min}(S_n))$, $\| \Phi_n \|^2 = o(n)$ a.s. which implies that f_n tends to zero a.s. Hence, by (B.2), we find that

$$\sum_{k=1}^{n} \| \pi_k \|^2 = \mathcal{O}(\log n) \quad \text{a.s.} \tag{B.12}$$

On the other hand, we obviously have from (B.1)

$$\| C_n - \Gamma_n \| = \mathcal{O}\left(\frac{1}{n}\sum_{k=1}^{n} \| \pi_{k-1} \|^2\right) \quad \text{a.s.} \tag{B.13}$$

Consequently, we immediately obtain the tracking optimality (4.2) from (B.12) and (B.13). Furthermore, by a well-known result of Lai and Wei [15] on the LS estimator, we also have

$$\| \widehat{\theta}_{n+1} - \theta \|^2 = \mathcal{O}\left(\frac{\log \lambda_{max} S_n}{\lambda_{min} S_n}\right) \quad \text{a.s.} \tag{B.14}$$

Hence (4.4) clearly follows from (B.11) and (B.14). Moreover, we also infer from Lemma 1 of Wei [17] together with (B.11) that

$$(\widehat{\theta}_{n+1} - \theta)^t S_n (\widehat{\theta}_{n+1} - \theta) = o(\log n) \quad \text{a.s.} \tag{B.15}$$

However, it follows from Theorem 4.3.16 part 4 of [9] that

$$\lim_{n\to\infty} \frac{1}{\log d_n}\left((\widehat{\theta}_{n+1} - \theta)^t S_n (\widehat{\theta}_{n+1} - \theta) + \sum_{k=0}^{n}(1 - f_k)\pi_k \pi_k^t\right) = \Gamma \quad \text{a.s.} \tag{B.16}$$

where $d_n = det(S_n)$. In addition, if $\delta = d(p+q)$, we deduce from (B.11) that

$$\lim_{n\to\infty} \frac{d_n}{n^\delta} = \det \Lambda \quad \text{a.s.} \tag{B.17}$$

Finally, (B.15) together with (B.16) and (B.17) imply (4.3), which achieves the proof of Theorem 4.1. □

Proof of Theorem 4.2. By Theorem 1 of [4], we have

$$\sum_{n=1}^{\infty} a_n (1 - f_n(a)) \| \pi_n \|^2 < +\infty \quad \text{a.s.} \tag{B.18}$$

where $f_n(a) = a_n \Phi_n^t S_n^{-1}(a) \Phi_n$. Then, as $a_n^{-1} = (\log(s_n))^{1+\gamma}$ with $\gamma > 0$, we clearly have $a_n^{-1} = \mathcal{O}(s_n)$ a.s. Hence, it follows from (B.18) together with Kronecker's Lemma given e.g. by Lemma 1.3.14 of [9] that

$$\sum_{k=1}^{n} \| \pi_k \|^2 = o(s_n) \quad \text{a.s.} \tag{B.19}$$

Therefore, we obtain from (3.4), (B.1) and (B.19) that

$$\sum_{k=1}^{n} \| X_{k+1} \|^2 = o(s_n) + \mathcal{O}(n) \quad \text{a.s.} \tag{B.20}$$

In addition, we also deduce from assumption (A$_1$) that

$$\sum_{k=1}^{n} \| U_k \|^2 = o(s_n) + \mathcal{O}(n) \quad \text{a.s.} \tag{B.21}$$

Consequently, we immediately infer from (B.20) and (B.21) that $s_n = o(s_n) + \mathcal{O}(n)$ so $s_n = \mathcal{O}(n)$ a.s. Hence, (B.19) implies that

$$\sum_{k=1}^{n} \| \pi_k \|^2 = o(n) \quad \text{a.s.} \tag{B.22}$$

Proceeding exactly as in Appendix A, we find from (B.22) that

$$\lim_{n\to\infty} \frac{S_n}{n} = \Lambda \quad \text{a.s.}$$

Via an Abel transform, it ensures that

$$\lim_{n\to\infty} (\log n)^{1+\gamma} \frac{S_n(a)}{n} = \Lambda \quad \text{a.s.} \tag{B.23}$$

We obviously have from (B.23) that $f_n(a)$ tends to zero a.s. Consequently, we obtain from (B.18) and Kronecker's Lemma that

$$\sum_{k=1}^{n} \parallel \pi_k \parallel^2 = o((\log s_n)^{1+\gamma}) \quad \text{a.s.} \tag{B.24}$$

Then, (4.6) clearly follows from (B.13) and (B.24). Finally, by Theorem 1 of [4]

$$\parallel \widehat{\theta}_{n+1} - \theta \parallel^2 = \mathcal{O}\left(\frac{1}{\lambda_{min} S_n(a)}\right) \quad \text{a.s.} \tag{B.25}$$

Hence, we obtain (4.7) from (B.23) and (B.25), which completes the proof of Theorem 4.2. □

Appendix C.

Proof of Theorem 4.3. First of all, it follows from (1.2) together with (3.1) that, for all $n \geq 1$,

$$\widehat{\theta}_n - \theta = S_{n-1}^{-1}(a) M_n(a) \tag{C.1}$$

where

$$M_n(a) = \widehat{\theta}_0 - \theta + \sum_{k=1}^{n} a_{k-1} \Phi_{k-1} \varepsilon_k^t. \tag{C.2}$$

We now make use of the CLT for multivariate martingales given e.g. by Lemma C.1 of [5], see also [9], [13]. On the one hand, for the LS algorithm, we clearly deduce (4.9) from convergence (4.1) and decomposition (C.1). On the other hand, for the WLS algorithm, we also infer (4.9) from convergence (4.5) and (C.1). Next, we make use of the LIL for multivariate martingales given e.g. by Lemma C.2 of [5], see also [9], [16]. For the LS algorithm, since (ε_n) has finite conditional moment of order $\alpha > 2$, we obtain from Chow's Lemma given e.g. by Corollary 2.8.5 of [16] that, for all $2 < \beta < \alpha$,

$$\sum_{k=1}^{n} \parallel \varepsilon_k \parallel^\beta = \mathcal{O}(n) \quad \text{a.s.} \tag{C.3}$$

Consequently, as the reference trajectory (x_n) satisfies (4.8), we deduce from (B.1) together with (B.12) and (C.3) that

$$\sum_{k=1}^{n} \parallel X_k \parallel^\beta = \mathcal{O}(n) \quad \text{a.s.} \tag{C.4}$$

Furthermore, it follows from (B.5) and (C.4) that

$$\sum_{k=1}^{n} \parallel U_k \parallel^\beta = \mathcal{O}(n) \quad \text{a.s.} \tag{C.5}$$

Hence, we clearly obtain from (C.4) and (C.5) that

$$\sum_{k=1}^{n} \| \Phi_k \|^{\beta} = \mathcal{O}(n) \quad \text{a.s.} \tag{C.6}$$

Therefore, as $\beta > 2$, (C.6) immediately implies that

$$\sum_{n=1}^{\infty} \left(\frac{\| \Phi_n \|}{\sqrt{n}} \right)^{\beta} < +\infty \quad \text{a.s.}$$

Finally, Lemma C.2 of [5] together with convergence (4.1) and (C.1) lead to (4.10). The proof for the WLS algorithm is left to the reader because it follows essentially the same arguments than the proof for the LS algorithm. It is only necessary to add the weighted sequence (a_n) and to make use of convergence (4.5). □

References

[1] K. J. Aström and B. Wittenmark, Adaptive Control, 2nd edition, Addison-Wesley, New York, 1995.
[2] B. Bercu, Sur l'estimateur des moindres carrés généralisés d'un modèle ARMAX. Application à l'identification des modèles ARMA. Annales de l'Institut Henri Poincaré, 27, (1991), pp. 425-443.
[3] B. Bercu and M. Duflo, Moindres carrés pondérés et poursuite, Annals de l'Institut Henri Poincaré, 28 (1992), pp. 403-430.
[4] B. Bercu, Weighted estimation and tracking for ARMAX models, SIAM J. Control Optim., 33 (1995), pp. 89-106.
[5] B. Bercu, Central limit theorem and law of iterated logarithm for least squares algorithms in adaptive tracking, SIAM J. Control Optim., 36 (1998), pp. 910-928.
[6] B. Bercu and B. Portier, Adaptive control of parametric nonlinear autoregressive models via a new martingale approach, IEEE Trans. Automat. Control, 47, (2002), pp. 1524-1528.
[7] P. E. Caines, Linear Stochastic Systems, John Wiley, New York, 1988.
[8] H. F. Chen and L. Guo, Identification and Stochastic Adaptive Control, Birkhäuser, Boston, 1991.
[9] M. Duflo, Random Iterative Models, Springer Verlag, Berlin, 1997.
[10] L. Guo and H. F. Chen, The Aström Wittenmark self-tuning regulator revisited and ELS-based adaptive trackers, IEEE Trans. Automat. Control, 36 (1991), pp. 802-812.
[11] L. Guo, Further results on least squares based adaptive minimum variance control, SIAM J. Control Optim., 32 (1994), pp. 187-212.
[12] L. Guo, Self convergence of weighted least squares with applications to stochastic adaptive control, IEEE Trans. Automat. Control, 41 (1996), pp. 79-89.
[13] P. Hall and C. C. Heyde, Martingale limit theory and its application, Academic Press, New York, 1980.
[14] R. A. Horn and C. R. Johnson, Matrix Analysis, Cambridge University Press, New York, 1990.
[15] T. L. Lai and C. Z. Wei, Extended least squares and their applications to adaptive control and prediction in linear systems, IEEE Trans. Automat. Control, 31 (1986), pp. 898-906.
[16] W. F. Stout, Almost sure convergence, Academic Press, New York, 1974.
[17] C. Z. Wei, Adaptive prediction by least squares predictors in stochastic regression models with applications to time series, Annals of Statistics, 15 (1987), pp. 1667-1682.

E-mail address: `Bernard.Bercu@math.u-bordeaux1.fr`
E-mail address: `Victor.Vazquez@siu.buap.mx`

Université Bordeaux 1, Institut de Mathématiques de Bordeaux, UMR 5251, 351 cours de la libération, 33405 Talence cedex, France.

Universidad Autónoma de Puebla, Facultad de Ciencias Fisico Matemáticas, Avenida San Claudio y Rio Verde, 72570 Puebla, Mexico.